

H800 Dual Color Hideaway Light



◆ Specifications

Voltage: DC 10 - 30 V

Amperage: 0.7 amps max per module at 12.8V

Dimensions: 1" H x 1½" Diameter Overall

◆ Wiring Instruction

Red Positive+, color 1

Green Positive+, color 2

Black Negative-, to Chassis ground

Amber --Flash pattern change and Synchronization

Blue -- Alternating

Note 1: Connect Red wire OR / AND Green wire to realize Alternating;

Click amber wire to Red OR/AND Green wires to change the flash patterns.

Note 2: Synchronization-- Connect Amber wires of all LED modules together at the same flash patterns for synchronization .

A. Apply 12V+ power to the red / Green wire and apply Ground to the black wire to turn the unit on.

B. Connect the red /Green wires of two or more light heads together; connect the black wires of two or more light heads together then hold the amber wire (flash pattern changer) to red /green wires for 3 seconds then take the amber wire away immediately, tapping the amber wire to the red / green wires, the steady burn pattern is selected .

C. Connect amber wires together to realize the synchronization .

Note 3 : Alternating---to sync two or more light heads together.

Follow A-B then tapping blue wire to red/green wire to realize alternating function .

◆ Flash Patterns

P1-Single 75 Ph1

P2-Single 75 Ph2

P3-Single 75 Alt

P4-Single 120 Ph1

P5-Single 120 Ph2

P6-Single 120 Alt

P7-Double 75 Ph1

P8-Double 75 Ph2

P9-Double 75 Alt

P10-Double 120 Ph1

P11-Double 120 Ph2

P12-Double 120 Alt

P13-Quad 75 Ph1

P14-Quad 75 Ph2

P15-Quad 75 Alt

P16-Quad 150 Ph1

P17-Quad 150 Ph2

P18-Quad 150 Alt

P19-Triple 75 Ph1

P20- Triple 75 Ph2

P21- Triple 75 Alt

P22-Quint 150 Ph1

P23-Quint 150 Ph2

P24-Quint 150 Alt

P25-Steady-Single

P26-Steady Burn

P27-Fast –Slow Modulation

P28-2 Double,2 Triple Alter

P29-4 Single,2 Quad

P30-Denary Left Flash

P31-Denary Right Flash

P32-Off

- Powered by 10-30V
- Each unit consists of 8 Pcs 3-watt high-intensity LEDs
- Dual color is available (amber-blue, amber-white, blue-white, red-blue, and red-white)
- 32 Flash Patterns with Pattern Memory
- Install the LED module into a 1" cut-out in the existing headlight or taillight lamp assembly or use the mounting flange to mount it to the vehicle surface wherever desired.
- Good for surface or internal mount within headlight, tail light, and various setups on personal emergency vehicles
- Multiple modules can be wired together for synchronized flash.

